
# Clamping Instructions



Ultra-Lok Free End

Warning: Always wear safety glasses when operating tool.


UL2000, UL4000, UL9000, UL9010 Ultra-Lok Tools:




- 1. Break off an Ultra-Lok Free-End tie from the roll. Slide the buckle onto band with indented arrows pointing in same direction and same side up. Slide buckle all the way onto band until it comes to a stop between the two buckle dimples at opposite end of tie.
- 2. wrap tie around object to be clamped. Insert the tie through buckle once for single-wrap or twice for double-wrap.



3. If desired, you may pre-form a clamp in the same fashion as step 2.



4. Position the tie on the object you are clamping. Pull the wrapped tie handtight.





Prepare Band-It Ultra-Lok tool for 5. Operate tool until proper tension operation as described in owners manual. With cut-off handle down as shown, insert clamp tail into tool head slot.



has been applied. Lift the cut-off handle to cut tail off and form a lock. Excess band can be removed by pulling out from rear of tool or reversing the drill.

6. Completed clamp should appear as shown.





BAND-IT-IDEX, Inc. A Unit of IDEX Corporation 4799 Dahlia Street Denver, CO 80216-3070 USA P: 1-800-525-0758 F: 1-800-624-3925

### www.BAND-IT-IDEX.com


Document # P07888 rev. F © Copyright BAND-IT-IDEX, Inc. 2006 All rights reserved

Page 1 of 2

## Clamping Instructions




Inspect buckle on completed clamp and tap down buckle shroud.



Important: Visually inspect lock formed in band as shown. If lock has slipped under the sheared surface of the buckle, remove clamp and install a new one at reduced tension by lowering the drill clutch torgue setting.

#### **Band and Buckle Totes:**



BAND-IT-IDEX, Inc. A Unit of IDEX Corporation 4799 Dahlia Street Denver, CO 80216-3070 USA P: 1-800-525-0758 F: 1-800-624-3925

#### www.BAND-IT-IDEX.com

Document # P07888 rev. F © Copyright BAND-IT-IDEX, Inc. 2006 All rights reserved